



TOWERVISION FONTS ARE NOW SUPPLIED WITH 7" WIDESCREEN UNITS AS STANDARD PLEASE SEE THE 7" W/S TOWERVISION INSTALLATION SHEET

TOWERVISION INSTALLATION INFORMATION (ALL 5.6" MODELS)

Towervision has been designed as 'Plug & Play'; Towervision Fonts are installed in exactly the same manner as any Font from the Porter Lancastrian Limited Standard Range.

It is the responsibility of the Site Operator to provide any line materials/media and media source to the Towervision font.

Porter Lancastrian Limited provides the 240v Mains /12V Dc Low Voltage Power Supply for connection to the BLACK colour coded female connector (This is one of the two female connectors to be found exiting from the base of the font clamp bracket) which powers the screen. Site is required to ensure that there is a suitably sited 240v supply to power the transformer.

The Ochre / Yellow colour coded female connector is used to carry a media signal (Standard Composite Video Signal) to the screen. It is possible to supply a standard composite video media signal to more than one Tower Vision Font; a Video Signal Amplifier (Booster) and or Router may be required for this operation.

Please ensure that both the Power & Signal connections are not left in such a way as to allow ingress of moisture/splashes/drips etc., we recommend fixing them to the underside of the bar top or other suitable location.

The supply and installation of ALL and any additional line materials, cable/plugs/ manifolds signal boosters etc is the responsibility of the Site Operator; this Equipment may be purchased from a suitable 'High Street' Retailer. If you are unsure of installation/set up and provision of media a suitably qualified person should be consulted

Towervision is covered by statutory warranty conditions as defined by the accompanying Font Information Sheet on a Return to Base condition.

Should a Towervision Screen cease to function i.e. go blank, please carry out the following tests before contacting your service provider:

- 1, Is the 12V Dc Power Supply cable securely plugged into the Black female connector?**
- 2, Check that the fuse has not failed in the 240 V ac Power Supply feed.**
- 3, Ensure that the Composite Video Cable is securely plugged into the Yellow Male connector.**
- 4, Check that the source of the Composite Video Signal has not failed / ceased to function.**

Should the Screen Still not function, the Screen Box with Cable attached and if possible the Power Supply should be returned to Porter Lancastrian Ltd either directly or via the original purchaser as a warranty claim.

Note: The Towervision Screen Box will be returned in the same condition as received, this warranty does not cover wear and tear to the outer faces of the Screen box.

TOWERVISION SERVICE EXCHANGE / SPARES INFORMATION (ALL MODELS)

Towervision **Service Exchange Units** (Electronic Assembly + Back Plate + Power Supply) can be purchased at **£ 185.00** per unit; this price is subject to the old unit being returned complete with the Power Supply.

New Towervision Screen Boxes complete with Power Supply can be purchased at **£ 245.00** per unit, please contact the Sales Office in either instance and specify which Font the Towervision Unit is to be fitted to.